

[第3表] ソリッドステートパワーアンプ用アッテネータの抵抗値表

Chriskit AT-19			Chriskit AT-816			Chrjskit AT-218		
Positions	Attenuation	Resistors	Attenuation	Resistors	Attenuation	Resistors		
10	(-0dB)	R-10=4.7K	(-0dB)	R-10=39K	(-0dB)	R-10=8.2K		
9	(-1dB)	R- 9=5.1K	(-8dB)	R- 9=5.6K	(-2dB)	R- 9=9.1K		
8	(-2dB)	R- 8=5.6K	(-9dB)	R- 8=5.6K	(-4dB)	R- 8=11K		
7	(-3dB)	R- 7=6.2K	(-10dB)	R- 7=5.6K	(-6dB)	R- 7=12K		
6	(-4dB)	R- 6=6.8K	(-11dB)	R- 6=5.1K	(-8dB)	R- 6=11K		
5	(-5dB)	R- 5=7.5K	(-12dB)	R- 5=4.7K	(-10dB)	R- 5=11K		
4	(-6dB)	R- 4=8.2K	(-13dB)	R- 4=3.9K	(-12dB)	R- 4=9.1K		
3	(-7dB)	R- 3=9.1K	(-14dB)	R- 3=3.6K	(-14dB)	R- 3=6.8K		
2	(-8dB)	R- 2=10K	(-15dB)	R- 2=3.0K	(-16dB)	R- 2=5.6K		
1	(-9dB)	R- 1=130K	(-16dB)	R- 1=20K	(-18dB)	R- 1=16K		
0	(∞)		(∞)		(∞)			